LBWS-5K

USER MANUAL

Http://www.lightbridge.co.kr

Office: (82) 31-5183-5228

Email: lightbridge.sales@gmail.com



Contents

1. Specification	p4.
2. Components	p5.
3. External Components	р6.
4. System Schematics	p8.
5. Initial Setup	p9.
6. Operation Method	p10.
7. Cautions	p19.
8. Components List	p19.



Introduction

This Manual was made for LBWS-5K model's installation, operation and User's convenience.

Please make sure read this manual from A-Z before operating the Electrolyzer and follow the manual so that it can work safely and correctly.



1. Specification



List	Contents	
Model name	LBWS-5K	
Electrolysis Type	Alkaline	
Size	L800 X W980 X H1,570 mm	
Input Voltage	380VAC 3phase	
Power consumption	<5kW	
os	Window 10	
Adjustable Pressure	Max 5 barg	
OperatingTemperature	e 10 ~ 65℃	
Max Flow rate	40SLM (H2), 20SLM (O2)	
Feed Water Type	Type I Distilled Water, KOH solution.	



2. Components

- ① Graphic panel It controls a hydrogen and oxygen generator while monitoring the overall system status.
- ② H2 Vent, O2 Vent, H2 Cool_Vent, O2 Cool_Vent (Solenoid valve)— As an electric valve, the valve opens and closes due to ON and OFF of electricity.
- ③ Gas/liquid separator Its function is to separate hydrogen and oxygen.
- 4 PLC Control board Controls the system operation.
- ⑤ PSU(Power Supply Unit) Provides DC power to the system.
- 6 Circulation Pump It circulates the water into the stack and gas/liquid separators.
- Water Pump It compensates externally the water consumption due to electrolysis.
- Water Out_Pump(water supply pump) It supplies external water when there is
 not enough water in the water tank.
- Peltier Fan(Peltier cooling system) It cools the gas from water electrolysis.
- ① Oxygen monitoring(option) It measures the Concentration of oxygen contained in hydrogen gas in real time.
- ① Computer and Monitor Those for controlling the system and saving the data.




3. External Components

Front Side



Front Panel












4. System Schematics





5. Initial Setup

- ① Power ONConnect the 380V 3phase power cable.(over than 4SQ size cable, R S T N and PE)
- 2 Turn on the power switch.
- 3 Turn the power and press the computer power.
- 4 When the computer turned on, Open the LB program.

 (The date files save in the next folder.)
- (5) Connect distilled water to the water supply line. (6mm tube)
- © Enter the Option mode, and press the Water Out_Pump button to inject distilled water until the W-LOW lamp turns off.(Already the separator filled with KOH)
- ② Go to option mode and press the Water Pump and check the Pump work correctly.(Inside of the system, you can find a cleared tube it must be filled with water)
- If H2 or O2 level is 0%, then go to the Option mode and press the Circulation Pump and Water Pump.
- (9) H2 and O2 level's difference should be less than 30%.
- For controlling the level, go to option mode and press H2 Vent and O2 Vent and Circulation Pump for an hour.
- ① Press the Water Pump to inject distilled water into the O2 water separator until the O2 Level reaches 30%. (It doesn't start when the sum of the levels of hydrogen and oxygen reaches 80% or W-Low turns on).


Light Bridge

6. Operation Method

Power ON

Connect the power cable.

- 2 Turn the power and press the computer power.
- ③ When the computer turned on, Open the LB program.
 (The date files save in the next folder.)



4 Computer program's screen.


This program provides status, data.

You can control the electrolyte's temperature, max pressure, apply voltages, currents, gas' cooling temperature (set point).

Data Acquisition Start: For recording the data to computer.



(Please Press the button after running the electrolyzer by touch panel or start button)



⑤ Programming

This tab is for controlling the voltage and the current.

All programs proceed sequentially and operate up to the entered program.


Duration means how long will the program operate.

Start voltage, current and End voltage, current controls the power supply at start value and end value gradually.

6 Graphic panel activation

Turn the power button on the right of the instrument.

- ⑦ Main display
- This screen provides basic status.



 H_2 : H_2 separator's status.

 O_2 : O_2 separator's status.

Water: Level of the water tank.

W-LOW: Indicates the low water level.

W-HIGH: Indicates the high water level.

Monitor: Each part turns on when it is working.

Pump Speed: Setting the water flow rates each of circulation pump1, 2.

DIN-V: Setting the applying voltages.

DIN-C: Setting the applying currents(amps).

Process Select: Operating the Electrolyzer easily.


Water Temp: indicates the electrolyte's temperature.

MFC(H₂, O₂): Indicates the flow rate of H₂ gas and O₂ gas

*Before start the system, please follow the initial setup.

Option Display





To configure the Option mode, press 'Option' below the touch panel.

 O_2 Pressure: Max means the system's maximum pressure and the set button can control the pressure of O_2 side. (If the pressure reach the set pressure, the system pause temporarily and reach the max, the system totally stop).

 H_2 Pressure: Max means the system's maximum pressure and the set button can control the pressure of H_2 side. (If the pressure reach the set pressure, the system pause temporarily and reach the max, the system totally stop).

Electrolyte Temp: Max means the System's maximum temperature of the KOH Solution in Celsius deg and the set button can control the temperature when will be the Separator Fan working.

Vent On/Off Timer: For setting the Solenoid Valve's on, off time.

MFC H2, O2: For controlling the output flow rate and indicates.

Manual Operation : You can operate each parts manually by pressing the button. (For reparing the Electrolyzer)

*(Don't operate only PSU, for operating the PSU,

Circulation pump must be on)



Monitor: Shows the hydrogen, oxygen separator's and water tank's solution level and other's level status.

Vent on. Vent off Timer: Setting the each side of valve's open and close time(over than 0.1 recommended).

Sensor Detecting

Hydrogen: for detecting the hydrogen gas leakages inside of the system.

Flow SW USE: When the system be broken or operate manually, press this button.

-If the flow switch doesn't work, please check the error code and solution.

Trouble would be caused by flexible tube then, please stretch the tube and check the pump speed.


You can set the pressure by two relief valves.(External valve is H₂ side and internal valve is O₂ side.)



The pressure of H2, O2 side must be almost same.

I/O Display





I/O Monitor: For monitoring whole parts connected to I/O in the system for operating.

*If you want to add any parts, you can use the empty side.

Alarm List





It shows the list when the Alarm have occurred.

After troubleshooting, if you want to remove the list, press the List Reset.

Emergency Alarm List

No.	Alarm List	Condition	Solution
EQ#[M900]	EQ#[M900] EMO_Alarm	Emergency Button is on	Make the Emergency button off
EQ#[M901]	EQ#[M901] Water_Tank_Alarm	Not enough water in water tank	Put Distilled Water to Water Tank manually (Water Out_Pump)
EQ#[M902]	EQ#[M902] Water_Pump_Alarm	Water Pump is on but, Separator Level is consistent over 5 minutes.	Stop and press the Reset button
EQ#[M903]	EQ#[M903] Stack_PSU_Alarm	O2 side consenser's level is high but, Power Supply is on	Turn off the system and wait for 30 seconds and turn on the system
EQ#[M904]	EQ#[M904] PSU_Siganl_Alarm-	Power supply sent a signal.	Turn off the system and wait for 30 seconds and turn on the system
EQ#[M905]	EQ#[M905] Temp_Sensor_Alarm	Solution's temperature is below 4 °C	Increase the ambient temperature
EQ#[M906]	EQ#[M906] [M]S_Pump_FlowSW_Alarm	The circulation pump works but, the flow swich is off	Stop and increase the pump speed. If same trouble occur, check the flow line(make it stretch)
EQ#[M907]	EQ#[M907] Oxygen_Sensing_Alarm	O2 gas in H2 is over the set ppm	Stop and refresh the system
EQ#[M908]	EQ#[M908] Hydrogen_Sensing_Alarm	H2 detected over the set %	Stop and refresh the system
EQ#[M909]	EQ#[M909] PSU_Output_Alarm	Power supply doesn't work over 30 seconds	Turn off the system and wait for 30 seconds and turn on the system
EQ#[M90A]	EQ#[M90A] Water_Pump_Fault_Alarm	When the Water_Pump doesn't work	Stop and go to option mode and press the Water_Pump and check the pump works water tank to separator



EQ#[M90B]	EQ#[M90B] O2_MAX_Pressure_Ala		O2 separator's p is over the Max	ressure	Stop and make the pressure below the max and press the reset button
EQ#[M90C]	EQ#[M90C] H2_MAX_Pressure_Ala		H2 separator's p is over the Max	ressure	Stop and make the pressure below the max and press the reset button
EQ#[M90D]	EQ#[M90D] Separator M Temp Alarm		Separator's temp is over the set	oerature	Stop and make the system cool down and press the reset button
EQ#[M90E]	EQ#[M90E] H2 Separator Level Max	It occurs What separator's over 65% maseconds		Stop and	press the Reset button
EQ#[M90F]	EQ#[M90F] H2 Separator Level LOW	It occurs What separator's under 15% seconds		Stop and	press the Reset button
EQ#[M910]	EQ#[M910] O2 Separator Level MAX	-It occurs W separator's over 65% m seconds	level keep	Stop and	press the Reset button
EQ#[M911]	EQ#[M911] O2 Separator Level LOW	It occurs What separator's under 15% seconds		Stop and	press the Reset button
EQ#[M912]	EQ#[M912] Separator level difference	separator's	eep over 20%	Stop and	press the Reset button
EQ#[M913]	EQ#[M913] Water Tank High_Manual	It occurs who Out_Pump wanually, at Tank's level	works nd Water	-	Nater Out_Pump and Reset button
EQ#[M914]	EQ#[M914] Auto Vent_Manual			Stop and	press the Reset button
EQ#[M920]	EQ#[M920] AD_Card_Err	or AD	Card make erro	r signal	Contact us
EQ#[M921]	EQ#[M921] TC_Card_Seting_Error		Card make sens	sor error	Contact us

EQ#[M922]	EQ#[M922] TC_Card_Solid_Wire_Error	TC Card make disconnection signal	Contact us
EQ#[M923]	EQ#[M923] DV_Card_Error	DV Card make error signal	Contact us
EQ#[M924]	EQ#[M924] PLC_Error	PLC make error signal	Contact us

^{*}If the trouble occurs repeatedly, Please contact us.

① Protection setup

The oxygen sensor measures the concentration of Oxygen gas. Oxygen Alarm Set will show when the concentration of Oxygen gas goes over the set. Hydrogen detection detects the sound of hydrogen in the water electrolysis device. In this screen, the oxygen concentration and the upper limit of the hydrogen volume are set to ensure the safety of electrolysis system.

- System Power off
- Front Panel Lights Mean

Status	Front Button Color
The Electrolyzer is on operating.	Green light on
The Electrolyzer has stopped.	Red light on
The Electrolyzer has interrupted with trouble.	Red and Green light simultaneously blinking
(Check the Electrolyzer's status through the panel and please follow the manual's Alarm List)	



7. Cautions

- If you want to completely shut down the system, keep the circulation pump and fan running until the water temperature drops to room temperature.
- Do not lay the electrolyzer by side or upside down.
- Do not disassemble or open the product.
- Please set the generation pressure of hydrogen and oxygen at least to 1 bar.
- Do not allow the setting of the water temperature to be above 65°C.
- If the water leaks, stop the operation and ask for customer support.
- Always keep the water supply port in the container filled with water.
- When the vent the gas, there could contain some water.
- Do not increase the pressure above 5 bar.
- We are not responsible if the above items are not observed or the equipment is modified arbitrarily.

8. Components List

- Condenser
- ② Gas/water separator
- ③ Circulation pump(Gear pump)
- ④ Diaphragm pump(Water pump)
- Solenoid pump(water pump)
- ⑥ Level transmitter
- (7) Pressure transmitter
- 8 Temperature sensor
- 9 Heat exchanger
- ① Hydrogen leak sensor
- ① Oxygen monitoring sensor(optional)
- Solenoid Valve
- ① MFC



* 1 Year Warranty (calculated from product received date) * Warranty void if unauthorized modification, disassemble or repairs attempted.
* Buyer's failure to comply with Seller's repair or replacement directions shall terminate Seller's obligations under this Warranty and render this
Warranty void.